R730

Indoor 802.11ax 8x8:8 Wi-Fi Access Point with Multi-gigabit backhaul



DATA SHEET



BENEFITS

CONNECT MORE DEVICES SIMULTANEOUSLY

Improve device performance, by enabling more simultaneous device connections with built-in 12 spatial streams (8x8:8 in 5GHz, 4x4:4 in 2.4GHz), MU-MIMO and OFDMA technology.

ULTRA-HIGH-DENSITY PERFORMANCE

Provides exceptional end-user experience within stadiums, large public venues, convention centers and school auditoriums with the Ruckus Ultra-High-Density Technology Suite.

ENHANCED SECURITY

Upgrade to the latest Wi-Fi security standard with WPA3 and receive enhanced protection from man-in-the-middle attacks in the most secure way.

MULTI-GIGABIT ACCESS SPEEDS

Optimized multi-gigabit Wi-Fi performance delivered using built-in 5GbE/2.5GbE Ethernet ports to connect to multi-gigabit switches.

DEVICE MANAGEMENT OPTIONS

Manage the R730 with on premise physical/virtual appliances and control auto-provisioning for faster deployment and seamless firmware upgrades.

BETTER MESH NETWORKING

Minimize complexity by reducing expensive cabling with SmartMesh™ that dynamically creates self-forming, self-healing mesh networks.

AUTOMATE OPTIMAL THROUGHPUT

ChannelFly[™] dynamic channel technology uses machine learning to automatically find the least congested channels. You always get the highest throughput the band can support.

MORE THAN WI-FI

Support services beyond Wi-Fi with <u>Ruckus</u> <u>IoT Suite</u>, <u>Cloudpath</u> security and onboarding software, <u>SPoT</u> Wi-Fi locationing engine, and <u>SCI</u> network

The R730 is based on the latest Wi-Fi standard, 802.11ax and bridges the performance gap from 'gigabit' Wi-Fi to 'multigigabit' Wi-Fi in support of the insatiable demand for better and faster Wi-Fi.

The Ruckus R730 is our highest capacity dual-band, dual-concurrent 802.11ax AP that supports 12 spatial streams (8x8:8 in 5GHz, 4x4:4 in 2.4GHz). The R730, with OFDMA and MU-MIMO capabilities, efficiently manages more than 1K client connections with increased capacity, improved coverage and performance in ultrahigh dense environments. Furthermore, 5 Gbps multi-gigabit Ethernet ports enhances backhaul capacity.

Additionally, the R730 is IoT- and LTE-ready, and supports wireless standards beyond Wi-Fi in combination with the Ruckus IoT Suite and our CBRS/OpenG modules.

The R730 addresses the increasing client demands in transit hubs, auditoriums, stadiums, conference centers, and other highly trafficked indoor spaces. It is the perfect choice for data-intensive streaming multimedia applications like 4K video transmissions, while supporting latency sensitive voice and data applications with stringent quality-of-service requirements.

The R730 when paired with the Ruckus Ultra-High density Technology Suite found only in the Ruckus Wi-Fi portfolio, dramatically improves network performance through a combination of patented wireless innovations and learning algorithms that includes:

- Airtime Decongestion: Increases average network throughput in heavily congested environments
- **Transient Client management:** Reduces interference traffic from unconnected Wi-Fi devices
- BeamFlex+ Antennas: Extended coverage and optimized throughput with patented multi-directional antennas and radio patterns

Whether you're deploying ten or ten thousand APs, the R730 is also easy to manage through Ruckus' appliance and virtual management options.

ACCESS POINT ANTENNA PATTERN

Ruckus' BeamFlex+ adaptive antennas allow the R730 AP to dynamically choose among a host of antenna patterns (over 4,000 possible combinations) in real-time to establish the best possible connection with every device. This leads to:

- Better Wi-Fi coverage
- Reduced RF interference

Traditional omni-directional antennas, found in generic access points, oversaturate the environment by needlessly radiating RF signals in all directions. In contrast, the Ruckus BeamFlex+ adaptive antenna directs the radio signals perdevice on a packet by-packet basis to optimize Wi-Fi coverage and capacity in real-time to support high device density environments. BeamFlex+ operates without the need for device feedback and hence can benefit even devices using legacy standards

Figure 1. Example of BeamFlex+ pattern




Figure 2. R730 2.4GHz Azimuth Antenna Patterns



Figure 3. R730 5GHz Azimuth Antenna Patterns



Figure 4. R730 2.4GHz Elevation Antenna Patterns





Figure 5. R730 5GHz Elevation Antenna Patterns



Note: The outer trace represents the composite RF footprint of all possible BeamFlex+ antenna patterns, while the inner trace represents one BeamFlex+ antenna pattern within the composite outer trace.

WI-FI	
Wi-Fi Standards	• IEEE 802.11a/b/g/n/ac/ax
Supported Rates	 802.11ax: 4 to 4800 Mbps 802.11ac: 6.5 to 3467 Mbps 802.11n: 6.5 to 600 Mbps 802.11a/g: 6 to 54 Mbps 802.11b: 1 to 11 Mbps
Supported Channels	• 2.4GHz: 1-13 • 5GHz: 36-64, 100-144, 149-165
МІМО	8x8 MU-MIMO 8x8 SU-MIMO
Spatial Streams	8 MU-MIMO 8 SU-MIMO
Channelization	• 20, 40, 80MHz
Modulation	OFDMA (up to 1024-QAM)
Security	WPA-PSK, WPA-TKIP, WPA2 AES, 802.11i, Dynamic PSK WIPS/WIDS
Other Wi-Fi Features	WMM, Power Save, TxBF, LDPC, STBC, 802.11r/k/vHotspot Hotspot 2.0 Captive Portal WISPr

RF	
Antenna Type	2.4GHz Antennas Omni: 2 Antennas BeamFlex+ Adaptive: 2 Antennas Polarization: 3 Vertical & 1 Horizontal SGHz Antennas Omni: 4 Antennas BeamFlex+ adaptive: 4 Antennas Polarization: 6 Vertical & 2 Horizontal
Antenna Gain (max)	• Up to 2 dBi
Frequency Bands	 2.4 - 2.484 GHz 5.17 - 5.33 GHZ 5.49 - 5.71 GHz 5.735 - 5.835 GHz

2.4GHZ R	2.4GHZ RECEIVE SENSITIVITY						
нт	20	нт	HT40		T20	VH	T40
MCS0	MCS7	MCS0	MCS7	MCS0	MCS7	MCS0	MCS7
-91	-73	-88	-70	-91	-73	-88	-70
	HE20				HE	40	
MCS0	MCS7	MCS9	MCS11	MCS0	MCS7	MCS9	MCS11
-91	-73	-68	-62	-88	-70	-65	-59

5GHZ	5GHZ RECEIVE SENSITIVITY										
	VHT20			VHT40			VHT80				
MCS0	MCS7	MCS8	MCS9	MCS0	MCS7	MCS8	MCS9	MCS0	MCS7	MCS8	MCS9
-91	-72	-69	_	-88	-69	_	-65	-85	-66	_	-62
	HE20				HE	40			HE	80	
MCS0	MCS7	MCS9	MCS11	MCS0	MCS7	MCS9	MCS11	MCS0	MCS7	MCS9	MCS11
-91	-72	-68	-62	-88	-69	-65	-59	-85	-66	-62	-56

2.4GHZ TX POWER TARGET (PER CHAIN)				
Rate	Pout (dBm) - Full Power	Pout (dBm) - 802.3at		
MCS0 HT20	20	20		
MCS7 HT20	16	16		
MCS8 VHT20	15	15		
MCS9 VHT40	14	14		
MCS11 HE40	12	12		

5GHZ TX POWER TARGET (PER CHAIN)				
Rate	Pout (dBm) - Full Power	Pout (dBm) - 802.3at		
MCS0 VHT20	22	22		
MCS7 VHT40, VHT80	16.5	16.5		
MCS9 VHT40, VHT80	15	15		
MCS11 HE20, HE40, HE80	12.5	12.5		

PERFORMANCE AND CAPACITY		
Peak PHY Rates	• 2.4GHz: 1.148 Gbps (11ax) • 5GHz: 4.8 Gbps (11ax)	
Client Capacity	Up to 1024 clients per AP	
Simultaneous VoIP Clients	• Up to 60 per AP	
SSID	Up to 16 per radio	

RUCKUS RADIO MANAGEMENT		
Antenna Optimization	BeamFlex+ PD-MRC	
Wi-Fi Channel Management	• ChannelFly	
Client Density Management	Band BalancingClient Load BalancingAirtime FairnessAirtime-based WLAN Prioritization	
Queuing & Scheduling	SmartCast	
Mobility	SmartRoam	
Diagnostic Tools	Spectrum Analysis SpeedFlex	
High Density Deployments (RF Innovations)	Perpacket Adaptive PowerAdaptive Wi-Fi Cell SizeTransient Client ManagementAirtime Decongestion	

NETWORKING	
Controller Platform Support	SmartZoneZDStandalone
Mesh	 SmartMesh[™] wireless meshing technology
IP	• IPv4, IPv6
VLAN	802.1Q BSSID-based (16 BSSIDs / radio) Port-based Dynamic, per user based on RADIUS
802.1x	Wired & wireless Authenticator & Supplicant
Tunnel	RuckusGRE, SoftGRE
Policy Management Tools	Application Recognition and Control Access Control Lists Device Fingerprinting

OTHER RADIO TECHNOLOGIES	
IoT	BLE, Zigbee

PHYSICAL INTERFACES		
Ethernet	1x 1/2.5/5 Gbps port, RJ-451x 10/100/1000 Mbps port, RJ-45	
USB	• 1 USB 2.0 port, Type A	

PHYSICAL CHARACTERISTICS		
Physical Size	• 22.19 x 24.96 x 6 cm • 8.74 x 9.83 x 2.36 in.	
Weight	• 1.53 kg • 3.37 lbs	
Mounting	Wall, Acoustic ceiling, Desk Secure Bracket (sold separately)	
Physical Security	Hidden Latching Mechanism	
Operating Temperature	• -0C (32F) to 50°C (122°F)	
Operating Humidity	• Up to 95%, non-condensing	

POWER CONSUMPTION				
Mode	Power Con- sumption	System Configuration	Wi-Fi Radios	
DC Power, PoH, uPoE (Idle)	16.1W	5Gbps & 1Gbps Ethernet enabled USB Enabled (3W) Zigbee/BLE Enabled (0.5W)	2.4GHz (4x4) enabled 5GHz (8x8) enabled (no clients associated)	
DC Power, PoH, uPoE (Max)	31.0W	5Gbps & 1Gbps Ethernet enabled USB Enabled (3W) Zigbee/BLE Enabled (0.5W)	2.4GHz (4x4) Tx 20 dBm 5GHz (8x8) Tx 22 dBm	
802.3at (Max)	23.8W	5Gbps & 1Gbps Ethernet enabledUSB Enabled (3W)Zigbee/BLE Disabled	2.4GHz (4x4) Tx 20 dBm 5GHz (4x4) Tx 22 dBm	
802.3af (Not re- commended)	12.4W	 5Gbps & 1Gbps Ethernet enabled USB disabled Zigbee/BLE Disabled	2.4GHz disabled 5GHz disabled	

CERTIFICATIONS AND COMPLIANCE		
Wi-Fi Alliance	 Wi-Fi CERTIFIED™ a, b, g, n, ac Passpoint® Vantage 	
Standards Compliance	 EN 60950-1 Safety EN 60601-1-2 Medical EN 61000-4-2/3/5 Immunity EN 50121-1 Railway EMC EN 50121-4 Railway Immunity IEC 61373 Railway Shock & Vibration EN 62311 Human Safety/RF Exposure UL 2043 Plenum WEEE & ROHS ISTA 2A Transportation 	

SOFTWARE AND SERVICES		
Location Based Services	• SPoT	
Network Analytics	SmartCell Insight (SCI)	
Security and Policy	Cloudpath	
IoT	Ruckus IoT Suite	

Indoor 802.11ax 8x8:8 Wi-Fi Access Point with Multi-gigabit backhaul

ORDERING INFORMATION		
901-R730-XX00	R730 dual-band (5GHz and 2.4GHz concurrent) 802.11ax wireless access point, Ultra-High Density performance, 12 spatial streams, adaptive antennas, PoE support. Includes adjustable acoustic drop ceiling bracket. Two Ethernet ports with 1GbE and 5Gbe. Does not include power adaptor	

PLEASE NOTE: When ordering Indoor APs, you must specify the destination region by indicating -US, -WW, or -Z2 instead of XX. When ordering PoE injectors or power supplies, you must specify the destination region by indicating -US, -EU, -AU, -BR, -CN, -IN, -JP, -KR, -SA, -UK, or -UN instead of -XX.

For access points, -Z2 applies to the following countries: Algeria, Egypt, Israel,

Morocco, Tunisia, and Vietnam.

OPTIONAL ACCESSORIES		
902-0180-XX00	PoE Injector (60W)	
902-1170-XX00	• Power Supply (48V, 0.75A, 36W)	
902-0120-0000	Spare, Accessory Mounting Bracket	

PLEASE NOTE: When ordering Indoor APs, you must specify the destination region by indicating -US, or -Winstead of XX. When ordering PoE injectors or power supplies, you must specify the destination region by indicating -US, -EU, -AU, -BR, -CN, -IN, -JP, -KR, -SA, -UK, or -UN instead of -XX.